

TCA 3727 G	Sie	LIN-IC	=TCA 3727: SMD	24-DIP	-	-
TCA 3728	Sie	LIN-IC	2Ph. Schritt-/Stepper Motor Drv, Ucc=5...50V, 1,5A	64-MP	-	-
TCA 4500(A)	Sie	LIN-IC	PLL Stereo-Decoder, Blend, o. Spulen/wo. Inductors	16-DIP	TCA 4500 A	16-DIP
TCA 4510	Sie	LIN-IC	Stereo-Decoder	18-DIP	-	LM 4500A, UL 1261N
TCA 4511(-2)	Aeg,Sie	LIN-IC	PLL Stereo-Decoder	18-DIP	-	A 4510D A 4511D
TCA 5500	Mot	LIN-IC	4x Audio Stereo-Potentiometer	18-DIP	-	-
TCA 5550	Mot	LIN-IC	4x Audio Stereo-Potentiometer	18-DIP	-	-
TCA 5600	Mot	LIN-IC	Netzteilsteuerung/PS Controller f. µP, 0...+125°	18-DIP	-	TCF 5600

TCE....TCH

TCF 5600	Mot	LIN-IC	=TCA 5600: -40...+150°	18-DIP	-	-
TCH 98(B)	Tag	Si-P	LF,S, 40V, 0,05A, 15MHz	2a	-	BC 212, BC 257, BC 307, BC 557, ++
TCH 99(B)	Tag	Si-P	=TCH 98: 70V	2a	-	BC 212, BC 256, BC 266, BC 556, ++

TD

TD		C-Di	=1SV262 (SMD-Marking)	71(1,7mm)	SOD-323		+1SV262	
TD		Si-Sensor	=KTY 13-D (SMD-Marking)	35	SOT-23			
TD 2,8F 400....800H	Aeg	F-Thy+Di	TV-HA, Hinlauf/Trace, 400...800V, 2,8A(Tc=80°), 8A= Igt/Ih<50<100mA, tq<2,9µs	22a	TO-66	TD 3FP 800H*	17f	BSiCC01...H, TD 3F...H, TD 4F...H
TD 2,8F 400....800R	Aeg	F-Thy+Di	=TD 2,8F...H: Rücklauf/Retrace, tq<5,1µs	22a	TO-66	TD 3FP 800R*	17f	BSiCC01...R, TD 3F...R, TD 4F...R
TD 3 F 400....800 H	Aeg	F-Thy+Di	=TD 2,8F...H: 3,4A(Tc=80°)	22a	TO-66	TD 3FP 800H*	17f	TD 4F...H
TD 3 F 400....800 R	Aeg	F-Thy+Di	=TD 2,8F...R: 3,4A(Tc=80°)	22a	TO-66	TD 3FP 800R*	17f	TD 4F...R
TD 3 FP 800 H	Aeg	F-Thy+Di	=TD 2,8F...H: 3,4A	17f	TO-220	TD 3FP 800H*	17f	BSiCC0253H, 17088
TD 3 FP 800 R	Aeg	F-Thy+Di	=TD 2,8F...R: 3,4A	17f	TO-220	TD 3FP 800R*	17f	BSiCC0253R, 17089
TD 4 F 400....800 H	Aeg	F-Thy+Di	=TD 2,8F...H: 4A(Tc=80°)	22a	TO-66	17088*	17f	BSiCC02...H, 17088
TD 4 F 400....800 R	Aeg	F-Thy+Di	=TD 2,8F...R: 4A(Tc=80°)	22a	TO-66	17089*	17f	BSiCC02...R, 17089
TD 5	Tho	50Hz-Thy	=2N1595: 500V	2a	TO-39			+2N1595
TD 6	Tho	50Hz-Thy	=2N1595: 600V	2a	TO-39			+2N1595
TD 041		Si-Di	=BA 157	31a		BA 159	31a	+BA 157
TD 62 C802F	Tos	MOS-IC	48-Bit Thermal Head Driver	64-MP				
TD 62 C804F	Tos	MOS-IC	32-Bit Thermal Head Driver	64-MP				
TD 62 C805F	Tos	MOS-IC	48-Bit Thermal Head Driver	64-MP				
TD 62 C806F	Tos	MOS-IC	32-Bit Thermal Head Driver	64-MP				
TD 62 C850N	Tos	Bi-CMOS-IC	16-Bit Shift Register, Latch, Driver	30-SDIP				
TD 62 C851N	Tos	Bi-CMOS-IC	8-Bit Shift Register, Latch, Driver	20-DIP				
TD 62 C852N	Tos	Bi-CMOS-IC	8-Bit Shift Register, Latch, Driver	20-DIP				
TD 62 C930...953	Tos	Bi-MOS-IC	SMD, Display Treiber/Driver					
TD 62 M3500F	Tos	LIN-IC	SMD, 3x PNP Trans., 10V, 2A	10-MDIP				
TD 62 M3501F	Tos	LIN-IC	SMD, 3x PNP Trans., 30V, 1,5A	10-MDIP				
TD 62 M3700F	Tos	LIN-IC	SMD, 3x PNP+ 3x NPN Trans., 30V, 1,5A	16-MDIP				
TD 62 M3701F	Tos	LIN-IC	SMD, 3x PNP+ 3x NPN Trans., 10V, 2A	16-MDIP				
TD 62 M4500F	Tos	LIN-IC	SMD, 4x NPN Trans., 10V, 2A	16-MDIP				
TD 62 M4600F	Tos	LIN-IC	SMD, 4x PNP Trans., 10V, 2A	16-MDIP				
TD 62 M4700F	Tos	LIN-IC	SMD, 2x Brückentreiber/Bridge Drv, 10V, 2A	16-MDIP				
TD 62 M8500F	Tos	LIN-IC	SMD, 8x NPN Trans., 10V, 2A	16-MDIP+b				
TD 62 M8600F	Tos	LIN-IC	SMD, 8x PNP Trans., 10V, 2A	16-MDIP+b				
TD 129	Itt	Si-Di	Uni, 50V, Uf<1,15V(0,1A)	31a		1N4148	31a	BA 127, BA 147/50, BA 215, 1N4148...49,++
TD 144		Si-St	=BZX 62	31a		1N4148	31a	+BZX 62
TD 147		Si-Di	=1N4148	31a		1N4148	31a	+1N4148
TD 153	Itt	Si-Di	Uni, 50V, 0,43...0,51V(0,1mA)	31a		1N4148	31a	BA 127, BA 147/50, BA 215, 1N4148...49,++
TD 175		Si-Di	=1N4148	31a		1N4148	31a	+1N4148
TD 176		Si-Di	=BA 157	31a		BA 159	31a	+BA 157
TD 184		Si-Di	=BY 127	31a		1N4007	31a	+BY 127
TD 190(A....C)		Si-Di	=BA 157	31a		BA 159	31a	+BA 157
TD 260		Si-Di	=BA 157	31a		BA 159	31a	+BA 159
TD 300		Si-Di	=BA 316	31a		1N4148	31a	+BA 316
TD 469		Si-Di	=1N4148	31a		1N4148	31a	+1N4148
TD 473		Si-Di	=BA 316	31a		1N4148	31a	+BA 316
TD 482		Si-Di	=1N4148	31a		1N4148	31a	+1N4148
TD 490		Si-Di	=BAY 21	31a		BA 159	31a	+BAY 21
TD 503	Ssc	50Hz-Thy	=BRY 54/30T: 50V	2a	TO-5			+BRY 54/30T
TD 702		Si-Di	=BAV 19	31a		BA 159	31a	+BAV 19
TD 861		Si-Di	=1N4148	31a		1N4148	31a	+1N4148
TD 1003	Ssc	50Hz-Thy	=BRY 54/100T:	2a	TO-5			+BRY 54/100T
TD 1011		Si-P	=BC 556	7c	TO-92	BC 556	7a	+BC 556
TD 1095	Tix	Si-Di	Uni, 35V, 0,05/0,15A, Uf<1V(10mA)	31a	DO-35	1N4148	31a	BA 127, BA 147/50, BA 215, 1N4148...49,++
TD 2003	Ssc	50Hz-Thy	=BRY 54/200T:	2a	TO-5			+BRY 54/200T
TD 3003	Ssc	50Hz-Thy	=BRY 54/300T:	2a	TO-5			+BRY 54/300T
TD 4003	Ssc	50Hz-Thy	=BRY 54/400T:	2a	TO-5			+BRY 54/400T
TD 5001 S	Ssc,Tho	50Hz-Thy	=2N2322: 500V	2a	TO-5, -39			+2N2322
TD 5003	Ssc	50Hz-Thy	=BRY 54/500T:	2a	TO-5			+BRY 54/500T
TD 6001 S	Ssc,Tho	50Hz-Thy	=2N2322: 600V	2a	TO-5, -39			+2N2322
TD 6003	Ssc	50Hz-Thy	=BRY 54/600T:	2a	TO-5			+BRY 54/600T
TD 6100 P	Tos	DIG-IC	Divider by 4 Counter					
TD 6101 P	Tos	ECL-IC	AM/FM Frequ.-Teiler/Prescaler, 1:8, 1:80, 1:88	14-DIP				
TD 6102 P	Tos	DIG-IC	AM/FM Frequ.-Teiler/Prescaler, 1:4, 1:8	9-SIP				
TD 6103 P	Tos	ECL-IC	TV, Frequ.-Teiler/Prescaler, 1:64					
TD 6104 P	Tos	DIG-IC	FM Frequ.-Teiler/Prescaler	7-SIP				
TD 6105 AP	Tos	ECL-IC	1GHz Frequ.-Teiler/Prescaler, 1:4	7-SIP				
TD 6106 AP	Tos	ECL-IC	1GHz Frequ.-Teiler/Prescaler, 1:8	7-SIP				
TD 6107 P	Tos	ECL-IC	1GHz Frequ.-Teiler/Prescaler, 1:64	7-SIP				
TD 6108 P	Tos	ECL-IC	1GHz Frequ.-Teiler/Prescaler, 1:256	7-SIP				
TD 6109 P	Tos	DIG-IC	AM/FM Frequ.-Teiler/Prescaler	7-SIP				
TD 6110 P	Tos	TTL-IC	1GHz Frequ.-Teiler/Prescaler, 1:64	7-SIP				
TD 6111 P	Tos	TTL-IC	1GHz Frequ.-Teiler/Prescaler, 1:256	7-SIP				
TD 6112 P	Tos	ECL-IC	1GHz Frequ.-Teiler/Prescaler, 1:128	7-SIP				
TD 6113 P	Tos	TTL-IC	1GHz Frequ.-Teiler/Prescaler, 1:128	7-SIP				
TD 6115 P	Tos	TTL-IC	1,2GHz Frequ.-Teiler/Prescaler, 1:64	7SIP, 8DIP				
TD 6116 P	Tos	TTL-IC	1,2GHz Frequ.-Teiler/Prescaler, 1:64	7SIP, 8DIP				
TD 6117 P	Tos	ECL-IC	1,2GHz Frequ.-Teiler/Prescaler, 1:64	7SIP, 8DIP				
TD 6118 P	Tos	ECL-IC	1,2GHz Frequ.-Teiler/Prescaler, 1:64	7SIP, 8DIP				
TD 6119 P	Tos	TTL-IC	1,2GHz Frequ.-Teiler/Prescaler, 1:128	7SIP, 8DIP				