

TDA 1365	Pls	LIN-IC	CTV, PAL Color Signal Processor	28-DIP				
TDA 1405	Sgs	Z-IC	+5V, 0,85A	14b	TO-126	7805/TO-220	17b	... 7805... (TO-126)
TDA 1410(A)(H,V)	Aeg,Sgs	LIN-IC	Audio Out, TV-VA Out, 36V, 3,5A	17/5Pin	TO-220/5			TDA 1420
TDA 1412	Sgs	Z-IC	+12V, 0,72A	14b	TO-126	7812/TO-220	17b	... 7812... (TO-126)
TDA 1415	Sgs	Z-IC	+15V, 0,6A	14b	TO-126	7815/TO-220	17b	... 7815... (TO-126)
TDA 1418	Sgs	Z-IC	+18V, 0,5A	14b	TO-126	7818/TO-220	17b	... 7818... (TO-126)
TDA 1420(A)(H,V)	Aeg,Sgs	LIN-IC	Audio Out, TV-VA Out, 44V	17/5Pin	TO-220/5			(TDA 1420L)
TDA 1420 L(LH,LV)	Aeg,Sgs	LIN-IC	=TDA 1420(H,V): 40V	17/5Pin	TO-220/5			TDA 1420
TDA 1424	Sgs	Z-IC	+24V, 0,35A	14b	TO-126	7824/TO-220	17b	... 7824... (TO-126)
TDA 1432 P	Phi	D/A-IC	8-Bit, TTL compatible					-
TDA 1470	Sgs	LIN-IC	TV, VA Os, Sync. Signal, VA Out	16-DIP+c				-
TDA 1470 A	Sgs	LIN-IC	=TDA 1470: Fig. >	16-DIP+d				-
TDA 1490	Sgs	LIN-IC	komplement. Darl Out, 55V, 3A, 30W, hFE=10000	17/5Pin	TO-220/5			-
TDA 1506	Phi	LIN-IC	Recorder, Motorsteuerung/Function Control	16-DIP				-
TDA 1508	Phi	LIN-IC	Recorder, Servo, Autoreverse Ctrl.	18-DIP				-
TDA 1510(A,AQ)	Phi	LIN-IC	Dual Audio Out, 18V, 6A, 2x12W(14V/2Ω)	13-QILP		TDA 1510	13-QILP	-
TDA 1512	Phi	LIN-IC	HiFi Audio Out, 35V, 3,2A, 25W(32V/4Ω)	9-SILP		TDA 1512(A)	9-SILP	-
TDA 1512 A	Phi	LIN-IC	=			TDA 1512(A)	9-SILP	-
TDA 1512 AQ,Q	Phi	LIN-IC	=TDA 1512: Fig. >	9-QILP		TDA 1512(A)	9-SILP	-
TDA 1514	Phi	LIN-IC	HiFi Audio Out, ±30V, ±4A, 40W(±27,5V/8Ω) RthG<1,5°/W	9-SILP		TDA 1514 A	9-SILP	-
TDA 1514 A	Phi	LIN-IC	=TDA 1514: RthG<1°/W	9-SILP		TDA 1514 A	9-SILP	-
TDA 1515(A,AQ)	Phi	LIN-IC	Dual Audio Out, 28V, 6A, 2x12W(14V/2Ω)	13-QILP		TDA 1515 A,AQ	13-QILP	-
TDA 1515 B,BQ	Phi	LIN-IC	=TDA 1515(A)	13-QILP		TDA 1515 A,AQ	13-QILP	-
TDA 1516 BQ	Phi	LIN-IC	=TDA 1516Q	13-QILP		TDA 1516 Q	13-QILP	(TDA 1518Q)
TDA 1516 CQ	Phi	LIN-IC	=TDA 1516Q: 1x22W(14,4V/4Ω)	13-QILP		TDA 1516 Q	13-QILP	-
TDA 1516 Q	Phi	LIN-IC	Dual Audio Out, 18V, 4A, 2x11W(14V/4Ω), 20dB	13-QILP		TDA 1516 Q	13-QILP	(TDA 1518Q)
TDA 1517	Phi	LIN-IC	Audio Out, 18V, 2,5A, 2x6W(14,4V/4Ω), 20dB	9-SIL/SQL				TDA 1519, TDA 1519B
TDA 1518 Q,BQ	Phi	LIN-IC	=TDA 1516Q,BQ: 40dB	13-QILP		TDA 1518 Q,BQ	13-QILP	-
TDA 1519	Phi	LIN-IC	=TDA 1517: 40dB	9-SIL,SQL				-
TDA 1519 A	Phi	LIN-IC	Dual Audio Out, 17,5V, 4A, 2x11W(14V/2Ω)	9-S(Q)ILP				-
TDA 1519 B	Phi	LIN-IC	=TDA 1519A: 2x6W(14,4V/4Ω)	9-SIL				-
TDA 1520	Phi	LIN-IC	HiFi Audio Out, 44V, 4A, 22W(33V/4Ω)	9-SILP		TDA 1520 A,B	9-SILP	TDA 1520A
TDA 1520 A	Phi	LIN-IC	=TDA 1520: 50V, RthG=2°/W	9-SILP		TDA 1520 A,B	9-SILP	-
TDA 1520 B	Phi	LIN-IC	=TDA 1520: 50V, RthG=2,5°/W	9-SILP		TDA 1520 A,B	9-SILP	TDA 1520A
TDA 1520(A,B)Q	Phi	LIN-IC	=TDA 1520(A,B): Fig. >	9-QILP				TDA 1520A,B
TDA 1521	Phi	LIN-IC	Dual HiFi Audio Out, ±20V, 4A, 2x15W(±16V/8Ω)	9-SILP		TDA 1521	9-SILP	-
TDA 1521 A	Phi	LIN-IC	=TDA 1521: 2x8W(±12V/8Ω)	9-SIL				-
TDA 1521 Q	Phi	LIN-IC	=TDA 1521: Fig. >	9-QILP		TDA 1521	9-SILP	TDA 1521(A)
TDA 1522	Phi	LIN-IC	Recorder, Dual Audio Inp	9-SIL		TDA 1522	9-SIL	-
TDA 1524	Phi	LIN-IC	Stereo Potentiometer f. Tone+Volume+Balance Ctrl.	18-DIP				A 1524D
TDA 1524 A	Phi	LIN-IC	=TDA 1524: modif. physiolog. Logic	18-DIP		TDA 1524 A	18-DIP	-
TDA 1525	Phi	LIN-IC	Stereo Potentiometer/Tone+Volume+Balance Ctrl.	18-DIP				-
TDA 1526	Phi	LIN-IC	Stereo Potentiometer/Tone+Volume+Balance Ctrl.	18-DIP				-
TDA 1527	Phi	LIN-IC	Dual OP-Amp.(Audio Umschaltg./Select)	9-SIL				-
TDA 1533	Phi	LIN-IC	PLL Motorregler/Motor Speed Control	18-DIP				-
TDA 1534	Phi	A/D-IC	14 Bit, Hi-Fi Audio	28-DIP				-
TDA 1535	Phi	LIN-IC	Sample & Hold f. A/D-Converter	16-DIP				-
TDA 1535 B	Phi	LIN-IC	Sample & Hold f. A/D-Converter	16-DIP				-
TDA 1537	Phi	LIN-IC	Stereo Sample & Hold f. A/D-Converter	16-DIP				-
TDA 1540 D	Phi	D/A-IC	=TDA 1540PN: SMD	28-MDIP				-
TDA 1540 P,PN	Phi	D/A-IC	14 Bit, serial Output, 0...+70°	28-DIP				-
TDA 1541(N)	Phi	D/A-IC	CD, Dual, 16 Bit, Digital Audio, Pin 16/17: nc.	28-DIP				-
TDA 1541 A,AN	Phi	D/A-IC	=TDA 1541: extern C osc (Pin 16/17)	28-DIP		TDA 1541 A,AN	28-DIP	-
TDA 1542	Phi	LIN-IC	CD, Tiefpassfilter/Low Pass Filter	28-DIP				-
TDA 1543(P)	Phi	D/A-IC	CD, Dual, 16 Bit, I²C Input, f. HiFi	8-DIP				-
TDA 1543 A	Phi	D/A-IC	=TDA 1543(P): Japan Input Format	8-DIP				-
TDA 1543(A)/S6	Phi	D/A-IC	=TDA 1543(A): Relaxed Version (low-cost)	8-DIP				-
TDA 1543 T, AT	Phi	D/A-IC	=TDA 1543(A): SMD	16-MDIP				-
TDA 1544(P)	Phi	D/A-IC	Dual, ra, 16 Bit f. HiFi Digital Audio	8-DIP				-
TDA 1544 T	Phi	D/A-IC	=TDA 1544(P): SMD	16-MDIP				-
TDA 1545	Phi	CMOS-D/A-IC	Stereo, Digital Audio, Continuous Calibration	8-DIP				-
TDA 1545 T	Phi	D/A-IC	=TDA 1545: SMD	8-MDIP				-
TDA 1547	Phi	D/A-IC	BIMOS, Dual, Bitstream DAC, Digital Audio	32-SDIP				-
TDA 1550	Tho	Z-IC	Tuner-Stab., 33V, (=ZTK 33)	31h		ZTK 33	31h	ZTK 33
TDA 1551 Q	Phi	LIN-IC	Quad Audio Out, 18V, 4A, 4x11W(14,4V/2Ω), I²C BTL: 2x22W(14,4V/4Ω)	17-QILP				-
TDA 1552 Q	Phi	LIN-IC	Dual Audio Out, 18V, 4A, 2x22W(14,4V/4Ω,BTL)	13-QILP				TDA 1553Q
TDA 1553 Q	Phi	LIN-IC	=TDA1552Q: Speaker Protection (Pin12)	13-QILP				-
TDA 1553 CQ	Phi	LIN-IC	=TDA 1553Q: 3-state Mode Switch	13-QILP				-
TDA 1554 Q	Phi	LIN-IC	Quad Audio Out, 18V, 4A, 4x11W(14,4V/2Ω) BTL: 2x22W(14,4V/4Ω)	17-QILP				-
TDA 1555 Q	Phi	LIN-IC	Quad Audio Out, 18V, 4A, 4x11W(14,4V/2Ω) BTL: 2x22W(14,4V/4Ω)	17-QILP				-
TDA 1556 Q	Phi	LIN-IC	Dual Audio Out, 18V, 4A, 2x22W(14,4V/4Ω,BTL)	17-QILP				-
TDA 1557 Q	Phi	LIN-IC	Dual Audio Out, 18V, 4A, 2x22W(14,4V/4Ω,BTL)	13-QILP				-
TDA 1558 Q	Phi	LIN-IC	Quad Audio Out, 18V, 4A, 4x11W(14,4V/2Ω) BTL: 2x22W(14,4V/4Ω)	17-QILP				-
TDA 1559(A)	Phi	LIN-IC	Motorregler/Motor Speed Control	14b				-
TDA 1571	Phi	LIN-IC	FM Tuner Modulator/Demodulator, sym	16-DIP				-
TDA 1571 T	Phi	LIN-IC	=TDA 1571: SMD	16-MDIP				-
TDA 1572	Phi	LIN-IC	AM Radio	18-DIP				-
TDA 1572 T	Phi	LIN-IC	=TDA 1572: SMD	20-MDIP				-
TDA 1574	Phi	LIN-IC	FM Tuner, IF, AGC	18-DIP				-
TDA 1574 T	Phi	LIN-IC	=TDA 1574: SMD	20-MDIP				-
TDA 1575 T	Phi	LIN-IC	FM Tuner, IF, AGC	16-MDIP				-
TDA 1576	Phi	LIN-IC	FM IF, Dem, AFC	18-DIP				-
TDA 1576 T	Phi	LIN-IC	=TDA 1576: SMD	20-MDIP				-
TDA 1578(A)	Phi	LIN-IC	PLL Stereo-Decoder	18-DIP		TDA 1578(A)	18-DIP	-
TDA 1579	Phi	LIN-IC	ARI Decoder/Traffic Warning Code Decoder(VWF)	18-DIP				-
TDA 1579 T	Phi	LIN-IC	=TDA 1579: SMD	20-MDIP				-
TDA 1580	Phi	LIN-IC	FM/TV Tuning, Suchlauf/Station Searching	18-DIP				-
TDA 1581 T	Phi	LIN-IC	SMD, ARI Decoder/Traffic Warning Code Decoder(VWF)	20-MDIP				-